



C09-EE-408

3479

BOARD DIPLOMA EXAMINATION, (C-09)

MARCH/APRIL—2016

DEEE—FOURTH SEMESTER EXAMINATION

ELECTRICAL ENGINEERING DRAWING

Time : 3 hours ]

[ Total Marks : 60

---

PART—A

5×4=20

**Instructions** : (1) Answer **all** questions.

(2) Each question carries **five** marks.

(3) Drawing should be neat with necessary dimensions.

1. Draw cross-sectional view of HRC fuse and label the parts.
2. Draw the sectional end view of a commutator assembly.
3. Draw a free-hand sketch of 132 kV tower for double circuit and mention the standard dimensions.
4. Draw a neat line diagram of a 132/33 kV substations layout and label.

/3479

1

[ Contd...

WWW.MANARESULTS.CO.IN

\*

**PART—B**

20×2=40

**Instructions** : (1) Answer *any two* questions.

(2) Each question carries **twenty** marks.

(3) Drawing should be neat with necessary dimensions.

**5.** (a) Draw the half-sectional end elevation looking from the shaft end of a 100 kW DC generator with the following data : 10

External diameter of armature stamping	: 42 cm
Internal diameter of armature stamping	: 20 cm
No. of slots	: 39
Size of slot	: 4 cm×1.2 cm
Height of pole	: 16 cm
Width of pole	: 12 cm
Interpole size	: 15 cm×4.5 cm
Air gap at main pole	: 0.5 cm
Air gap at interpole	: 0.7 cm
Thickness of yoke	: 6.8 cm

Note : Assume any other missing data.

(b) Develop a 3- lap winding for an a.c. machine having 24 slots, 4 poles and one conductor per slot. 10

**6.** Draw the following views of a 3-phase, 250 kVA, 11 kV/400 V transformer : 20

(a) Front elevation full in section

(b) Plan full in section

The detailed dimensions of the parts are as follows :

Core :

1. Cross-section of the core : 3-step core
2. Dia of the circum-circle : 24 cm
3. Distance between the adjacent of centres core : 42.5 cm

Yoke :

Yoke height : 25 cm

*LT Winding :*

1. Outside diameter of LT coil : 28.3 cm
2. Inside diameter of LT coil : 25 cm
3. Height of LT winding : 43.5 cm
4. Number of turns per phase : 12

*HT Winding :*

1. Outside diameter of HT coil : 41.5 cm
2. Inside diameter of HT coil : 34.3 cm
3. Height of HT winding : 43.5 cm
4. Number of turns per phase : 572

Total height of the transformer : 100 cm

Note : Other missing data may be assumed.

7. Draw the following views of a 7.5 h.p., 400 V, 50 Hz, 3-phase, 1440 r.p.m. slip-ring induction motor : 20

(a) Half-sectional front elevation

(b) Half-sectional end view

The main dimensions have been given below :

1. Outside diameter of the stator stamping : 288
2. Inside diameter of the stator stamping : 216
3. Stator core length : 106
4. Thickness of the stator frame : 31
5. Slots :
  - (a) Type : Open type
  - (b) Number : 36
  - (c) Size : 8×12
6. Air gap : 2
7. Outside diameter of the rotor stamping : 212
8. Inside diameter of the rotor stamping : 36
9. Rotor core length : 106

10. Slots : \*
- (a) Type : Open type
  - (b) Number : 36
  - (c) Size : 12×8
11. Shaft diameter :
- (a) At centre : 36
  - (b) At bearing : 32
12. Ducts :
- (a) Stator frame : 8
  - (b) Rotor : 4
  - (c) Spacing between ducts : equally spaced

Note: All the dimensions are in mm.

Assume any other missing dimensions.

\*\*\*

\*