



C16-EE-106

6040

**BOARD DIPLOMA EXAMINATION, (C-16)
SEPTEMBER/OCTOBER - 2020
DEEE—FIRST YEAR EXAMINATION
BASIC ELECTRICAL ENGINEERING**

Time : 3 hours]

[Total Marks : 80

PART—A

3×10=30

Instructions : (1) Answer **all** questions.

(2) Each question carries **three** marks.

(3) Answers should be brief and straight to the point and shall not exceed *five* simple sentences.

1. State Ohm's law and give the equation.
2. Define temperature coefficient of resistance and state its unit.
- * 3. Define work, power and energy.
4. State Joule's law of heat.
5. State right-hand thumb rule.
6. Define the following :
 - (a) MMF
 - (b) Flux
 - (c) Reluctance

/6040

1

[Contd...

7. Classify various ^{*} types of induced e.m.fs.
8. State Fleming's right-hand rule.
9. Define capacitance and state its unit.
10. State Gauss theorem.

PART—B

10×5=50

Instructions : (1) Answer *any five* questions.

(2) Each question carries **ten** marks.

(3) Answers should be comprehensive and the criterion for valuation is the content but not the length of the answer.

11. (a) State the effect of temperature on resistance. 3
 (b) The resistance of copper winding of a motor at room temperature of 20 °C is 3 42 . After an extended operation of the motor at full load, the winding resistance increases to 4 22 . Find the temperature rise. Given that the temperature coefficient of copper at 0 °C is 0.00426/°C. 7
12. (a) Define (i) EMF and (ii) resistance. State their units. 4
 (b) Derive an expression of equivalent resistance when three resistors are connected in parallel. 6
13. An industry is connected with the following loads :
 (i) 10 fans of 60 W each working for 10 hours a day
 (ii) 2 kW heater working for 6 hours a day
 (iii) 1 oven of 1.5 kW working for 6 hours a day
 (iv) 15 electric bulbs of 60 W each working for 4 hours a day
 Calculate the electricity bill for the month of 30 days at the rate of 55 paise per unit.

14. Draw a neat sketch of electric iron and explain different parts.
15. (a) Compare electric and magnetic circuits in any five aspects. 5
(b) State Laplace law. 5
16. (a) State and explain Faraday's laws of electromagnetic induction. 7
(b) State Lenz's law. 3
17. (a) Derive the equation for energy stored in a magnetic field. 5
(b) A coil of 600 turns carrying a current of 10 A gives rise to a magnetic flux of 1 mWb. Calculate the energy stored in the coil. 5
18. (a) Derive the equivalent capacitance when two capacitors are connected in series. 5
(b) Define dielectric strength and dielectric constant. 5

*