

Code No: 126AM**JAWAHARLAL NEHRU TECHNOLOGICAL UNIVERSITY HYDERABAD****B. Tech III Year II Semester Examinations, December - 2017****REFRIGERATION AND AIR CONDITIONING****(Mechanical Engineering)****Time: 3 hours****Max. Marks: 75****Note:** This question paper contains two parts A and B.

Part A is compulsory which carries 25 marks. Answer all questions in Part A. Part B consists of 5 Units. Answer any one full question from each unit. Each question carries 10 marks and may have a, b, c as sub questions.

PART - A**(25 Marks)**

- 1.a) What is the difference between Refrigeration and Air Conditioning? [2]
- b) Draw the line diagram of simple vapour compression refrigeration system. [3]
- c) What are the advantages of multistage compressor? [2]
- d) What are different types of expansion devices [3]
- e) Discuss the advantages of the dense air refrigerating system over an open air refrigeration system. [2]
- f) What are desirable characteristics of absorbent in vapour absorption refrigeration cycle? [3]
- g) Prove that the partial pressure of water vapour in the atmospheric air remains constant as long as the specific humidity remains constant. [2]
- h) Distinguish sensible and latent heat loads. [3]
- i) Classify Air conditioning systems. [2]
- j) Distinguish clearly fan and blower. [3]

PART - B**(50 Marks)**

- 2.a) Mention the limitations of Simple vapour compression refrigeration cycle.
- b) Briefly explain the working of two stage compression with water intercooler and liquid sub-cooler employed for vapour compression system. [5+5]

OR

- 3.a) Explain the construction and use of P-H charts in refrigeration system.
- b) Define C.O.P. How C.O.P of refrigerators and heat pump can be evaluated? Explain. [5+5]

- 4.a) How does an actual vapour compression cycle differ from that of a theoretical cycle?
- b) A vapour compression refrigeration machine, with Freon-12 as refrigerant, has a capacity of 12 tonne of refrigeration operating between -28°C and 26°C . The refrigerant is sub cooled by 4°C before entering the expansion valve and the vapour is superheated by 5°C before leaving the evaporator. The machine has a six-cylinder single-acting compressor with stroke equal to 1.25 times the bore. It has a clearance of 3% of the stroke volume. Determine (i) Theoretical power required, (ii) C.O.P, (iii) Volumetric efficiency, (iv) Bore and stroke of cylinder. The speed of compressor is 1000 r.p.m. the following properties of Freon-12 may be used. [5+5]

OR

- 5.a) Explain the working of following types of evaporators with neat sketches:
(i) Flooded evaporator, (ii) Natural convection evaporator.
- b) Give the comparison between air cooled and water cooled condenser. [5+5]
6. An air refrigerator working on Bell-Coleman cycle takes in air at 1 bar and at a temperature of 10°C . The air is compressed to 5 bar abs. The same is cooled to 25°C in the cooler before expanding in the expansion cylinder to cold chamber pressure of 1 bar. The compression and expansion laws followed are $PV^{1.35} = C$ and $PV^{1.3} = C$ respectively. Determine C.O.P of the plant and net refrigeration effect per kg of air. Take $C_p = 1.009 \text{ kJ/kg K}$ and $R = 0.287 \text{ kJ/kg K}$ for air. [10]

OR

7. A Two stage ammonia refrigeration system operates between overall pressure limits of 15 bar and 2 bar respectively. The liquid is sub-cooled to 30°C . The temperature of superheated vapour leaving the water intercooler is also 30°C . The flash chamber separates the dry vapour at 5 bar pressure. The liquid refrigerant then expands to 2 bar, the evaporator pressure. The load on the evaporator is 50 kW. Calculate a) Mass flow rate in different lines b) Power required c) COP. [10]
- 8.a) Explain the procedure for calculating cooling load due to infiltration air.
- b) A summer air conditioning system for a small office building is to be designed. The design is to be based on the following information:
Outside design condition 35°C Tdb, 28°C Twb
Inside design condition 26°C Tdb, 50% RH
Room sensible heat gain 45 kW
Room latent heat gain 9 kW
Ventilation air $0.95 \text{ m}^3/\text{s}$
A four row direct expansion refrigerant 134a coil with bypass factor of 0.2 is to be used. Analyze the problem on a psychometric chart and determine the following:
i) The room apparatus dew point (ADP)
ii) The temperature of the air leaving the coil
iii) The total quantity of air required (m^3/s). [5+5]

OR

9. The following data apply to an air conditioning system:
Room sensible heat = 41868 kJ/hr (11.63 kW); room latent heat = 41868 kJ/hr (11.63 kW);
inside design condition = 25°C , 50% RH, outside design condition = 35°C , DBT, 27.8 WBT . Return air from the room is mixed with the outside air before entering the cooling coil in the ratio of 4:1. Return air from the room is mixed with the cooling air, i.e. after the cooling coil in the ratio of 1:4. Cooling coil by pass factor is 0.1. The air may be reheated if necessary before supplying to the conditioned space. Assume ADP as 10°C and determine,
a) Supply air conditions into the room
b) Refrigeration load due to the reheat
c) Total refrigeration capacity
d) The quantity of fresh air supplied. [10]
- 10.a) Explain the use of HEAT PUMP for heating and cooling cycle with neat diagram.
- b) Explain in detail different components of fans. [5+5]
- 11.a) Describe a centrifugal fan with the help of a neat sketch.
- b) Explain in detail about heat pump circuits. [5+5]